




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : H04N 7/16, 7/167	A1	(11) International Publication Number: WO 95/29560 (43) International Publication Date: 2 November 1995 (02.11.95)
(21) International Application Number: PCT/US95/03540 (22) International Filing Date: 15 March 1995 (15.03.95) (30) Priority Data: 232,794 22 April 1994 (22.04.94) US (71) Applicant: THOMSON CONSUMER ELECTRONICS, INC. [US/US]; 10330 North Meridian Street, Indianapolis, IN 46290-1024 (US). (72) Inventors: TAMER, Gregory, George; 8447 Castle Ridge Lane, Indianapolis, IN 46256 (US). DEISS, Michael, Scott; 1103 Indian Pipe Lane, Zionsville, IN 46077 (US). CHANEY, John, William; 18019 Sunridge Circle, No- blesville, IN 46060 (US). HAILEY, James, Edwin; 7239 Creekside Lane, Indianapolis, IN 46250 (US). (74) Agents: TRIPOLI, Joseph, S. et al.; GE & RCA Licensing Management Operation, Inc., CN 5312, Princeton, NJ 08540 (US).		(81) Designated States: BR, CA, CN, JP, KR, MX, SG, European patent (AT, BE, CH, DE, DK, ES, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE). Published <i>With international search report.</i>

(54) Title: CONDITIONAL ACCESS INFORMATION ARRANGEMENT**(57) Abstract**

Apparatus in a receiver, for processing transmitted entitlement control information, includes a packet transport processor (13-15, 19) for selecting signal packets having payloads containing a conditional access payload header and a remaining payload of entitlement data. Respective payload headers include groups of bytes which are coded in a manner to allow or disallow the respective receiver from processing the entitlement data. A conditional access filter (30) preprogrammed with a subscriber specific conditional access codeword examines respective byte groupings of the conditional access header for a match with the subscriber specific conditional access codeword. Only if a match occurs is the processor permitted to process (17, 18, 21-24) the entitlement data. The entitlement data is thereafter utilized to generate (31) decryption keys for descrambling (16) portions of the transmitted signal.

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AT	Austria	GB	United Kingdom	MR	Mauritania
AU	Australia	GE	Georgia	MW	Malawi
BB	Barbados	GN	Guinea	NE	Niger
BE	Belgium	GR	Greece	NL	Netherlands
BF	Burkina Faso	HU	Hungary	NO	Norway
BG	Bulgaria	IE	Ireland	NZ	New Zealand
BJ	Benin	IT	Italy	PL	Poland
BR	Brazil	JP	Japan	PT	Portugal
BY	Belarus	KE	Kenya	RO	Romania
CA	Canada	KG	Kyrgystan	RU	Russian Federation
CF	Central African Republic	KP	Democratic People's Republic of Korea	SD	Sudan
CG	Congo	KR	Republic of Korea	SE	Sweden
CH	Switzerland	KZ	Kazakhstan	SI	Slovenia
CI	Côte d'Ivoire	LI	Liechtenstein	SK	Slovakia
CM	Cameroon	LK	Sri Lanka	SN	Senegal
CN	China	LU	Luxembourg	TD	Chad
CS	Czechoslovakia	LV	Latvia	TG	Togo
CZ	Czech Republic	MC	Monaco	TJ	Tajikistan
DE	Germany	MD	Republic of Moldova	TT	Trinidad and Tobago
DK	Denmark	MG	Madagascar	UA	Ukraine
ES	Spain	ML	Mali	US	United States of America
FI	Finland	MN	Mongolia	UZ	Uzbekistan
FR	France			VN	Viet Nam
GA	Gabon				

CONDITIONAL ACCESS INFORMATION ARRANGEMENT

5 This invention relates to apparatus for processing packets of program component data from a packet video signal and more particularly to circuitry for detecting packet payloads to which a subscriber has conditional access for entitlement information.

10 It is known from, for example, United States Patent No. 5,168,356 and United States Patent No. 5,289,276, that it is advantageous to transmit compressed video signal in packets, with respective packets affording a measure of error protection/correction. The systems in the foregoing patents
15 transmit and process a single television program, albeit with a plurality of program components, from respective transmission channels. These systems utilize inverse transport processors to extract the video signal component of respective programs for further processing to condition the video component for
20 reproduction.

 It is known, from for example, *THE SATELLITE BOOK, A COMPLETE GUIDE TO SATELLITE TV THEORY AND PRACTICE*, Swift Television Publications, 17 Pittsfield, Cricklade, Wilts, England, that transmitted television signal reception can be
25 limited to particular subscribers by scrambling the signal. The limitations may be altered at the will of the broadcaster by periodically transmitting different entitlement data. The entitlement data is processed by smart cards located in respective receivers to generate decryption or descrambling keys, for use by
30 decryption or descrambling devices in only those receivers entitled to reproduce the associated program material. In a packet video system of the aforementioned type, entitlement data may be included in specific packets which are recognizable as containing such data for easy access by smart card circuitry.

35 A large area broadcast system, such as a direct broadcast satellite system targeted for North America, will have very large numbers of subscribers. This number will be so large

as to preclude changing the entitlement data of specific receivers on very short notice. Consider, for example, that a broadcaster is
5 required to black out the area local to a sports stadium in the event that tickets for the sporting event are not sold out. This information may not be available until immediately before the event. The broadcaster of course will want to wait until the last possible minute before making the decision to black out the local
10 region. The present invention provides a method and apparatus whereby entitlement data is layered to provide denial of entitlements to receive program material on short notice.

The present invention is a system/method for layered entitlement data transmission/reception. A receiver embodiment
15 includes a packet transport processor for selecting packets having payloads containing a conditional access payload header and a remaining payload of entitlement data. Respective payload headers include groups of bytes which are coded in a manner to allow or disallow the respective receiver from processing the
20 entitlement data. A conditional access filter preprogrammed with a subscriber specific conditional access codeword examines respective byte groupings of the conditional access header for a match with the subscriber specific conditional access codeword. Only if a match occurs is the processor permitted to process the
25 entitlement data.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention will be described with reference to the drawings, wherein:

FIGURE 1 is a pictorial representation of a time
30 division multiplexed packet television signal;

FIGURE 2 is a pictorial representation of respective signal packets;

FIGURE 3 is a block diagram of a receiver for selecting and processing packets of multiplexed component signals
35 embodying the present invention;

FIGURE 4 is a block diagram of a conditional access filter/start code detector;

5 FIGURE 5 is a flow chart of the conditional access filter operation;

FIGURE 6 is a block diagram of an alternative conditional access filter;

10 FIGURE 7 is a block diagram of exemplary memory management circuitry which may be implemented for element 17 of FIGURE 3;

FIGURE 8 is a pictorial representation showing memory address formation for service channel data.

15 FIGURE 9 is a flow chart of operation of the memory address control.

FIGURE 1 shows a packet signal stream consisting of a string of boxes which represent signal packets that contain components of a plurality of different television or interactive television programs. These program components are assumed to be formed of compressed data and as such the quantity of video data for respective images is variable. The packets are of fixed length. Packets with letters having like subscripts represent components of a single program. For example, V_i , A_i , D_i represent video, audio and data packets and packets designated V_1 , A_1 , D_1 , 20 represent video, audio and data components for program 1, and V_3 , A_{31} , A_{32} , D_3 , represent video, audio 1, audio 2 and data components of program 3. The data packets D_i may contain e.g. control data to initiate certain action within a receiver, or they may include executable code forming an application to be 25 executed by e.g., a microprocessor located within or associated with a receiver. 30

In the upper line of the string of packets the respective components of a particular program are shown grouped together. However there is no necessity of packets from the same 35 program being grouped as is indicated by the entire string of

packets. Nor is there any particular order for the sequence of occurrence of respective components.

- 5 The respective packets are arranged to include a prefix and a payload as shown in FIGURE 2. The prefix of this example includes two 8-bit bytes comprising five fields, four (P, BB, CF, CS) of which are 1-bit fields, and one (SCID) of which is a 12-bit field. The SCID field is the signal component identifier.
- 10 The field CF contains a flag to indicate whether the payload of the packet is scrambled, and the field CS contains a flag which indicates which of two alternative unscrambling keys is to be utilized to unscramble scrambled packets. The prefix of every packet is packet aligned, thus the location of the respective fields
- 15 are easily identifiable.

- Within every payload is a header which contains a continuity count, CC, modulo 16, and a TOGGLE flag bit which are program component specific. The continuity count is simply a successive numbering of sequential packets of the same program
- 20 component. The TOGGLE flag bit is a one bit signal which changes logic level or toggles on the occurrence of a picture layer start code in an MPEG compressed video component.

- FIGURE 3 illustrates in block form, a portion of a digital television signal receiver including elements of an inverse
- 25 transport processor. Signal is detected by an antenna 10 and applied to a tuner detector, 11, which extracts a particular frequency band of received signals, and provides baseband compressed signal in a binary format. The frequency band is selected by the user through a microprocessor 19 by conventional
- 30 methods. Nominally broadcast digital signals will have been error encoded using, for example, Reed-Solomon forward error correcting (FEC) coding. The baseband signals will thus be applied to a FEC decoder, 12. The FEC decoder 12 synchronizes the received video and provides an error corrected stream of signal
- 35 packets of the type illustrated in FIGURE 1. The FEC 12 may provide packets at regular intervals, or on demand, by for

example, memory controller 17. In either case a packet framing or synchronizing signal is provided by the FEC circuit, which
5 indicates the times that respective packet information is transferred from the FEC 12.

The detected frequency band may contain a plurality of time division multiplexed programs in packet form. To be
10 useful, only packets from a single program should be passed to the further circuit elements. In this example it is assumed that the user has no knowledge of which packets to select. This information is contained in a program guide, which in itself is a program consisting of data which interrelates program signal components through SCID's, and may include information relating
15 to, for example, subscriber entitlements. The program guide is a listing for each program, of the SCID's for the audio, video, data etc. components of respective programs. The program guide (packets D4 in FIGURE 1) is assigned a fixed SCID. When power is applied to the receiver, the microprocessor 19 is programmed to
20 load the SCID associated with the program guide into one of a bank of similar programmable SCID registers 13. The SCID fields of the prefix portion of respective detected packets of signal from the FEC 12 are successively loaded in a further SCID register 14. The programmable registers and the received SCID register are
25 coupled to respective input ports of a comparator circuit 15, and the received SCID is compared with the program guide SCID. If the SCID for a packet matches the program guide SCID, the comparator 15 conditions a memory controller 17 to route that packet to a predetermined location in the memory 18 for use by
30 the microprocessor. If the received SCID does not match the program guide SCID, the corresponding packet is simply dumped.

The microprocessor waits for a programming command from the user via an interface 20, which is shown as a
35 computer keyboard, but which may be a conventional remote control, or receiver front panel switches. The user may request to view a program provided on channel 4 (in the vernacular of

analog TV systems). The microprocessor 19 is programmed to scan the program guide list that was loaded in the memory 18 for the respective SCID's of the channel 4 program components, and to
5 load these SCID's in respective other ones of the programmable registers of the bank of registers 13 which are associated with corresponding component signal processing paths.

Received packets of audio, video or data program
10 components, for a desired program, must ultimately be routed to the respective audio 23, video 22, or auxiliary data 21, (24) signal processors respectively. The data is received at a relatively constant rate, but the signal processors nominally require input data in bursts (according to the respective types of decompression
15 for example). The exemplary system of FIGURE 3, first routes the respective packets to predetermined memory locations in the common memory 18. Thereafter the respective processors 21-24 request the component packets from the memory 18. Routing the components through the common memory provides a measure of
20 desired signal data rate buffering or throttling.

The audio, video and data packets are loaded into respective predetermined memory locations to enable the signal processors convenient buffered access to the component data. In order that the payloads of respective component packets are
25 loaded in the appropriate memory areas, the respective SCID comparators are associated with those memory areas. This association may be hardwired in the memory controller 17, or the association may be programmable. If the former, specific ones of the programmable registers 13 will always be assigned the audio,
30 video and data SCID's respectively. If the latter, the audio, video and data SCID's may be loaded in any of the programmable registers 13, and the appropriate association will be programmed in the memory controller 17 when the respective SCID's are loaded in the programmable registers.

35 In the steady state, after the program SCID's have been stored in the programmable registers 13, the SCID's of

received signal packets are compared with all of the SCID's in the programmable SCID registers. If a match is made with either a
5 stored audio, video or data SCID, the corresponding packet payload will be stored in the audio, video or data memory area or block respectively.

The respective signal packets are coupled from the FEC
12 to the memory controller 17 via a signal decryptor 16. Only
10 the signal payloads are scrambled and the packet headers are passed by the decryptor unaltered. Whether or not a packet is to be descrambled is determined by the CF flag in the packet prefix, and how it is to be descrambled (one of two alternative descrambling keys) is determined by the CS flag. If no SCID
15 match is had for a respective packet, the decryptor may simply be disabled from passing any data.

The decryptor is programmed with decryption keys provided by the smart card apparatus 31. The smart card is responsive to entitlement information contained in particular
20 packets of the program guide to generate appropriate decryption keys. The system of the present example incorporates two levels of encryption or program access, entitlement control messages, ECM's, and entitlement management messages, EMM's. Program entitlement control and management information is regularly
25 transmitted in packets identifiable with specific SCID's included in the packet stream comprising the program guide. The ECM information contained in these packets is used by the smart card to generate the decryption keys used by the decryptor. The EMM information included in these packets is used by the subscriber
30 specific smart card to determine program material to which the subscriber is entitled. EMM entitlement information within these packets may be made geographically specific, or group specific or subscriber specific. For example, the present system will include a modem (not shown) for communicating billing information from
35 the smart card to the program provider, e.g., the satellite broadcaster. The smart card may be programmed with, for

example, the area code and telephone exchange of the receiver location. The EMM may include data, which when processed by
5 the smart card, will entitle or deny reception of particular programs in particular area codes.

The program provider may want the ability to entitle certain subscribers with very short lead time, as for example for pay-per-view programs. The identification of particular
10 subscribers may not be available until shortly before airing of the particular program. With such short lead time it may not be possible to program EMM's on a subscriber basis. A further layer of coding may be instantly impressed on the entitlement information by including a conditional access code to
15 permit/prohibit reception of the EMM and ECM data within respective packets, and thereby allow substantially instant permission/prohibition to certain programs.

Packet payloads containing the EMM and ECM entitlement data include a payload header of 128 bits arranged in
20 specially coded 4 groups of 32 bits. Each of the groups is coded with a conditional access code and each conditional access code may be coded differently. Each subscriber is assigned a specific conditional access code. A matched filter or E-code decoder 30, is arranged to detect a subscriber specific bit pattern within the 128
25 bit header. If a match is detected the decoder communicates with the memory controller 17 and the smart card 31 to make the remainder of the entitlement payload available to the smart card (via the memory 18). If a match is not detected, the payload is not accepted by the specific receiver. The conditional access codes
30 may be periodically changed if the matched filter 30 is made programmable. These codes may be periodically provided by the smart card. For more specific details on smart card operation as related to viewer entitlements the reader is invited to review Section 25 of THE SATELLITE BOOK, A COMPLETE GUIDE TO
35 SATELLITE TV THEORY AND PRACTICE..

The matched filter or E-code decoder is arranged to perform a second function, which is to detect particular MPEG video headers. These headers are 32-bit start codes, (which is the reason the headers of entitlement payloads are coded in 32-bit groups). If video data is lost, an MPEG video decoder can only restart decompressing video data at particular data entry points. These entry points coincide with MPEG start codes. The decoder may be arranged to communicate with the memory controller 17 to inhibit the flow of video data to memory after video packet losses, and to resume writing video payloads to memory only after the next MPEG start code is detected by the decoder 30.

FIGURE 4 illustrates exemplary apparatus for detecting packets which include conditional access information or MPEG start codes (decoder 30 of FIGURE 3). Whether the decoder 30 is conditioned to detect entitlement payloads or MPEG start codes is a function of the SCID currently being received. In FIGURE 4, it is assumed that data provided from the decryptor 16 is in 8-bit bytes and packet aligned. That is, the first byte of an entitlement payload or the first byte of an MPEG start code is aligned precisely with a particular byte position, e.g., the beginning of a packet payload, such that for detecting specific header or start codewords, their position in the bit/byte stream is precisely known. Data from the decryptor 16 is applied to an 8-bit register 250, which has an 8-bit parallel output port coupled to respective first input connections of a comparator 254 which may be configured of, for example, a bank of eight two-input exclusive NOR (XNOR) circuits having respective output connections coupled to an AND gate and a latch. The latch may be a data latch arranged to latch the results of the AND gate at each byte interval.

A 32-bit MPEG start code is stored as four bytes in an 8-bit register bank 265. Conditional access codes are stored as 8-bit bytes in a bank of 16 8-bit registers 257. Loading of the register banks 251 and 265 is controlled by the microprocessor 19 and/or by the smart card. The start code registers 265 are

coupled to a four to one multiplexer 266, and the conditional access code registers are coupled to a sixteen to one multiplexer 257. Output ports of the multiplexers 257 and 266 are coupled to a two to one multiplexer 249. Respective output connections of the multiplexer 249 are coupled to respective corresponding second input terminals of the comparator 254. (Note the input and output connections of the multiplexers 249, 257 and 266 are 8-bit busses.) If the respective values exhibited at the respective output connections of the register 250 are correspondingly the same as the output values exhibited by the respective output connections of the multiplexer 249, a true signal is generated by the comparator 254 circuit for the corresponding data byte.

For start code detection, the multiplexer 266 is scanned by the counter 258 to sequentially couple the four different registers 265 to the comparator in synchronism with the occurrence of the first four payload data bytes from the decryptor 16. Alternatively, for conditional access code detection, the multiplexer 257 is scanned by the counter 258 to sequentially couple different ones of the registers 265 to the comparator circuit 254.

The output of the comparator circuit is applied to an accumulate and test circuit 255. The circuit 255 determines if any of a predetermined number of byte matching conditions have occurred, and if they have, it generates a write enable signal for the entitlement data in the remaining portion of the particular payload under examination. In the present system the entitlement payload header contains 128 bits arranged in four 32-bit conditional access codes. The conditional access filters of different subscribers will be arranged to look for different combinations of bytes of the 128 bits. For example one subscriber apparatus may be arranged to match the first four bytes of the conditional access codes. Another subscriber apparatus may be arranged to match the second four bytes of the conditional access codes and so forth. In either of these exemplary situations the

circuitry 255 will determine if a match has occurred for the appropriate four consecutive bytes.

5 The use of 16 registers in the bank for a subscriber specific conditional access codes somewhat simplifies the circuit structure. Since each subscriber has a four byte conditional access code, the code may be loaded four times in the set of 16 registers. At the transmitter, the broadcaster need not then be concerned
10 about the relative location, with respect to the four groups of four bytes, of the conditional access codes being transmitted. An alternative arrangement may incorporate only a single group of four registers to hold the subscriber specific conditional access code, and these registers may be repeatedly scanned, modulo four,
15 through the 128 bits of the entitlement payload header.

 It is not practical to transmit each of the 2^{32} possible entitlement codes for every function, as this would undesirably limit the system bandwidth for other services and would also simply take too much time. This limitation may be somewhat
20 alleviated by arranging the conditional access code according to some logical groupings, wherein the groupings are defined by three bytes of respective four byte conditional access codes. In this manner all subscribers in a group may be addressed by conditioning respective receivers of the group to ignore one byte
25 of the four byte conditional access code. In this instance each four byte access code will represent 256 subscribers. The filter conditioning is effected by sending for example all zeroes in the first four byte positions and arranging the conditional access filter to detect this condition. If the condition is satisfied, the
30 conditional access filter is electrically restructured to detect a match of only three bytes of respective groups of four bytes.

 A third variant is provided to permit all subscribers conditional access. This is effected by coding the entitlement payload header with all zeroes (or all ones). The conditional
35 access filter is therefore arranged to also include an all zero detector (elements 261-263).

The bits of respective arriving bytes of data are coupled to respective terminals of the 8-bit OR gate 263. If any one of the bits is a logic one the OR gate 263 generates a logic one output. The output of the OR gate 263 is coupled to one input of a two-input OR gate 262, which has an output and second input coupled respectively to the data-input and Q-output terminals of a D-type latch 261. The D-type latch is clocked by the timing circuit 259 synchronously with the arrival of incoming data bytes. If any bit in any of the data bytes which occurs after the latch is reset is a logic one, the latch 261 will exhibit a logic one at its Q-output until the next reset pulse. The Q-output of latch 261 is coupled to an inverter which exhibits a zero output level whenever the latch exhibits a one output level. Thus, if after the 128 bits (16 bytes) of the header have been passed through register 250, the output of the inverter is high, then the 128 bits are zero valued. The latch is reset prior to the reception of each new payload. Responsive to detection of a high output level from the inverter after passage of the entitlement payload header, the circuitry 255 will generate a data write enable signal.

FIGURE 5 is a flow chart of the operation of the conditional access filter 30. The process is started by the detection of the associated SCID. Once the appropriate SCID has been detected the payload is applied {300} to the filter 30. A comparison {302} is made of the first four bytes of the header with the subscriber specific conditional access code. If a match occurs, an entitlement data write enable is generated {310}. If not the first four bytes are examined {306} for all zeroes. If all zeroes are not detected, the second four bytes of the header are compared {308} with the subscriber specific conditional access code. If they match {312}, a write enable is generated {310}. If not the third set of four bytes is compared {314} with the subscriber specific conditional access code. If they match {316}, a write enable is generated {310}. If not, the fourth set of four bytes is compared {317} with the subscriber specific conditional

access code. If they match {318}, a write enable is generated {310}. If not, the last 12 bytes of the header are examined for all zeroes {320}. If all zeroes are detected in the last 12 bytes, a write enable is generated {310} and if not a write enable is not generated and the process waits {300} for the next packet. In an alternative arrangement, at step {320} the system may be programmed to look for all zeroes in all 16 bytes of the header. It should also be appreciated that some other fixed pattern may be utilized other than all zeroes, such as all ones or an alternating pattern of zeroes and ones for example

At step {306} if the first four bytes are all zeroes, three of the second four bytes of the header are compared {354} with the subscriber specific conditional access code. In the FIGURE 4 apparatus this may be accomplished by arranging the element 255 to look for three matches for exclusive groups of four bytes. If three of the four bytes match {326} a write enable is generated {322} and if not, three of the third set of four header bytes are compared {330} with the subscriber specific conditional access code. If three of the four bytes match {332}, a write enable is generated {322}, and if not, three of the last four bytes are compared {336} with the subscriber specific conditional access code. If they match, a write enable is generated {322} and if not the all zero condition is examined {320}.

Note a further level of detection may be incorporated similar to the steps {324-340} where only two of respective groups of four bytes are matched. This may be conditioned by arranging the first eight bytes to be all zeroes or the first four bytes to be all ones, for example. In this instance the respective groups being enabled by the conditional access codes becomes much larger.

Regarding storing entitlement payloads in the memory 18, the system writes the payload header to memory as it is received and examined for conditional access codes. If a conditional access code is detected, the write enable which is

detected simply allows the memory control to continue writing the payload. Conversely if a conditional access code is not
5 detected within the first 16 bytes of the payload, the remainder of the payload is not written to memory, and the memory address for a conditional access payload is reset to overwrite the 16 bytes of payload conditional access header.

FIGURE 6 is an alternative conditional access filter
10 which compares as many as 32 bits (four bytes) at a time. This permits detection of start codes without foreknowledge of the byte position of the start code. The start code is stored in 8-bit registers 265. (Eight bit registers are used because an 8-bit μ PC bus is employed.) The output ports of the registers are coupled to
15 a first set of inputs of a multiplexer 298. The subscriber specific conditional access code is stored in a second register bank 299, which have respective output ports coupled to a second set of inputs to the multiplexer 298. The multiplexer 298 has a set of outputs connected to respective first 8-bit input ports of
20 comparators 270-273. Whether the output ports of registers 265 or 299 are coupled to the comparators is controlled by the accumulate and test circuitry 297 responsive to the μ PC.

Input bytes from the decryptor 16 are coupled to the parallel/serial registers 274-277. The respective registers 274-
25 277 have parallel output ports coupled respectively to second 8-bit input ports of the comparators 270-273. The system is timed such that four successive bytes of the input signal are currently loaded into the registers 274-277. The output terminals of the comparators are coupled to the accumulate and test circuit
30 297 via respective OR gates 278-281. Second input terminals of the OR circuits are coupled to respective control output connections of the accumulate and test circuit 297.

As in the FIGURE 4 apparatus, the apparatus of FIGURE 6 includes an all zeroes detector 261-263 for detecting all zeroes
35 in the first four bytes and all sixteen bytes.

For four byte conditional access code detection, successive exclusive groups of four bytes are loaded into the registers 274-277 and tested against the subscriber specific conditional access code contained in the registers 299. If all four comparators detect a match, the AND gate 283 produces a logic one indicating a match. If one of the comparators fails to detect a match the AND gate produces a logic zero. For three out of sets of four input byte conditional access code detection, the accumulate and test circuit 297 applies a logic one value to one of the control lines coupled to the OR gates. This forces the output of that OR gate to a logic one, effectively forcing a match from the associated comparator. Conditional access code detection is then performed on successive exclusive groups of four bytes as for four byte detection.

For start code detection, the control lines of all of the OR gates are held at a logic zero. Input bytes are sequentially applied to the cascade connection of registers 274-277 and a test for match with the start code stored in the registers 265 is made on each successive inclusive set of four input bytes.

FIGURE 7 illustrates exemplary apparatus for the memory controller 17 shown in FIGURE 3. Each program component is stored in a different contiguous block of the memory 18. In addition other data, such as data generated by the microprocessor 19 or the Smart Card (not shown) may be stored in the memory 18.

Addresses are applied to the memory 18 by a multiplexor 105, and input data is applied to the memory 18 by a multiplexor 99. Output data from the memory management circuitry is provided to the signal processors by a further multiplexor 104. Output data provided by the multiplexor 104 is derived from the microprocessor 19, the memory 18 or directly from the multiplexor 99. Program data is presumed to be of standard picture resolution and quality, and occurring at a particular data rate. On the other hand high definition television

signals, HDTV, which may be provided by this receiver, occur at a significantly higher data rate. Practically all data provided by the
5 FEC will be routed through the memory 18 via the multiplexer 99 and memory I/O circuit 102, except for the higher rate HDTV signals which may be routed directly from the multiplexer 99 to the multiplexer 104. Data is provided to the multiplexer 99 from the decryptor 16, the smart card circuitry, the microprocessor 19,
10 and a source of a media error codes 100. The term "media error codes as used herein, means special codewords to be inserted in a data stream, to condition the respective signal processor (decompressor) to suspend processing until detection of a predetermined codeword such as a start code, and then to resume
15 processing in accordance with the e.g. start code.

Memory addresses are provided to the multiplexer 105, from program addressing circuitry 79-97, from the microprocessor 19, from the Smart Card apparatus 31 and from the auxiliary packet address counter 78. Selection of the particular
20 address at any particular time period is controlled by a direct memory access DMA, circuit 98. The SCID control signals from the comparator 15 and "data needed" signals from respective signal processors are applied to the DMA 98, and responsive thereto, memory access contention is arbitrated. The DMA 98 cooperates
25 with a Service Pointer Controller 93, to provide the appropriate read or write addresses for respective program signal components.

The respective addresses for the various signal component memory blocks are generated by four groups of
30 program component or service pointer registers 83, 87, 88, and 92. The starting pointers for respective blocks of memory, into which respective signal components are stored, are contained in registers 87 for the respective signal components. The start pointers may be fixed values, or they may be calculated by
35 conventional memory management methods in the microprocessor 19.

Pointers for the last address of respective blocks are stored in the bank of service registers 88, one for each potential
5 program component. Similar to the start addresses, the end or last addresses may be fixed values or they may be calculated values provided by the microprocessor 19. Using calculated values for starting and end pointers is preferred because it provides a more versatile system with less memory.

10 The memory write pointers or head pointers are generated by the adder 80 and the service head registers 83. There is a service head register for each potential program component. A write or head pointer value is stored in a register 83, and provided to the address multiplexor 105 during a memory
15 write cycle. The head pointer is also coupled to the adder 80, wherein it is incremented by one unit, and the incremented pointer is stored in the appropriate register 83 for the next write cycle. The registers 83 are selected by the service pointer controller, 93, for the appropriate program component currently
20 being serviced.

In this example it is assumed that the start and end pointers are 16-bit pointers. The registers 83 provides 16 bit write or head pointers. 16-bit pointers were selected to facilitate use of 16-bit or 8-bit busses for loading the start and end pointers
25 in the registers 87 and 88. The memory 18, on the other hand, has 18-bit addresses. The 18-bit write addresses are formed by concatenating the two most significant bits of the start pointers to the 16-bit head pointers, with the start pointer bits in the most significant bit positions of the combined 18-bit write address. The
30 start pointers are provided by the respective registers 87 to the service pointer controller 93. The service pointer controller parses the more significant start pointer bits from the start pointers stored in registers 87, and associates these bits with the 16-bit head pointer bus. This is illustrated by the bus 96 shown
35 being combined with the head pointer bus exiting the multiplexor 85, and by FIGURE 8 with reference to the bold arrows.

In FIGURE 8, the top middle and bottom rows of boxes represent the bits of a start pointer, an address and a head or tail pointer respectively. The higher numbered boxes represent more significant bit positions. The arrows indicate from which bit positions of the start or head/tail pointers the respective bits of an address are derived. In this derivation the bold arrows represent steady state operation.

Similarly, memory read pointers or tail pointers are generated by the adder 79 and the service tail registers 92. There is a service tail register for each potential program component. A read or tail pointer value is stored in a register 92, and provided to the address multiplexor 105 during a memory read cycle. The tail pointer is also coupled to the adder 79, wherein it is incremented by one unit, and the incremented pointer is stored in the appropriate register 92 for the next read cycle. The registers 92 are selected by the service pointer controller, 93, for the appropriate program component currently being serviced.

The registers 92 provides 16 bit tail pointers. 18-bit read addresses are formed by concatenating the two most significant bits of the start pointers to the 16-bit tail pointers, with the start pointer bits in the most significant bit positions of the combined 18-bit write address. The service pointer controller parses the more significant start pointer bits from the start pointers stored in registers 87, and associates these bits with the 16-bit tail pointer bus. This is illustrated by the bus 94 shown being combined with the tail pointer bus exiting the multiplexor 90.

Data is stored in the memory 18 at the calculated address. After storing a byte of data, the head pointer is incremented by one and compared to the end pointer for this program component, and if they are equal the more significant bits of the head pointer are replaced with the lower 14 bits of the start pointer and zeros are placed in the lower two bit positions of the head pointer portion of the address. This is illustrated in

FIGURE 8 with reference to the hatched arrows between the start pointers and the address. This operation is illustrated by the
5 arrow 97 pointing from the service pointer controller 93 to the head pointer bus from the multiplexor 85. It is presumed that application of the lower 14 start pointer bits override the head pointer bits. Replacing the head pointer bits with the lower start pointer bits in the address for this one write cycle, causes the
10 memory to scroll through the memory block designated by the upper two start pointer bits, thus obviating reprogramming write addresses at the start of each packet to a unique memory location within a block.

If the head pointer ever equals the tail pointer (used
15 to indicate where to read data from the memory 18) a signal is sent to the interrupt section of the microprocessor to indicate that a head-tail crash has occurred. Further writing to the memory 18 from this program channel is disabled until the microprocessor re-enables the channel. This case is very rare and should not occur
20 in normal operation.

Data is retrieved from the memory 18 at the request of the respective signal processors, at addresses calculated by the adder 79 and registers 92. After reading a byte of stored data, the tail pointer is incremented by one unit and compared to the
25 end pointer for this logical channel in the service pointer controller 93. If the tail and end pointers are equal then the more significant bits of the tail pointer are replaced with the lower 14 bits of the start pointer and zeros are placed in the lower two bit positions of the tail pointer portion of the address. This is
30 illustrated by the arrow 95 emanating from controller 93 and pointing to the tail pointer bus from the multiplexor 90. If the tail pointer is now equal to the head pointer, then the respective memory block is defined as empty and no more bytes will be sent to the associated signal processor until more data is received from
35 the FEC for this program channel. The actual replacement of the head or tail pointer portions of the respective write or read

addresses by the lower 14 bits of the start pointer may be accomplished by appropriate multiplexing, or the use of three
5 state interconnects.

Memory read/write control is performed by the service pointer controller and direct memory access, DMA, elements 93 and 94. The DMA is programmed to schedule read and write cycles. Scheduling is dependent upon whether the FEC
10 12 is providing data to be written to memory or not. FEC data write operations take precedence so that no incoming signal component data is lost. In the exemplary apparatus illustrated in FIGURE 7, there are four types of apparatus which may access the memory. These are Smart Card, the FEC 12 (more precisely the
15 decryptor 16), the microprocessor 19 and the application devices such as the audio and video processors. Memory contention is handled in the following manner. The DMA, responsive to data requests from the various processing elements listed above, allocates blocks of memory for respective program components.
20 Access to the memory is provided in 95 nS time slots during which a byte of data is read from or written to the memory 18. There are two major modes of access allocation, defined by "FEC Providing Data", or "FEC Not Providing Data" respectively. For each of these modes the time slots are allocated and prioritized as
25 follows, assuming a maximum FEC data rate of 5 Mbytes/second, or one byte for each 200 nS. These are:

FEC Providing Data

- 1) FEC data write;
 - 2) Application device read/Microprocessor read/write;
 - 30 3) FEC data write;
 - 4) Microprocessor read/write;
- and for

FEC Not Providing Data

- 1) Smart Card read/write;
- 35 2) Application device read/Microprocessor read/write;
- 3)Smart Card read/write;

4) Microprocessor read/write.

5 Because FEC data writes cannot be deferred, the FEC (or more correctly the decryptor), when providing data must be guaranteed memory access during each 200 nS interval. Alternate time slots are shared by the application devices and the microprocessor. When there is no data available for the requesting devices, the microprocessor is provided use of the application time slots.

10 The Controller 93 communicates with the SCID detector to determine which of the respective Start, head and end pointer registers to access for memory write operations. The controller 93 communicates with the DMA to determine which of the start, end and tail registers to access for memory read
15 operations. The DMA 98 controls selection of the corresponding addresses and data by the multiplexers 99, 104 and 105.

FIGURE 9 illustrates an exemplary flow chart of the DMA 98 memory access process. The DMA responds {200} to detection or non detection of a received packet via detection of
20 SCID's. If a SCID has been detected indicating the presence of data from the decryptor 16 to be written to memory, one byte of program data from the decryptor is written {201} to the buffer memory 18. The block of memory to which it is written is determined by the processor 93 responsive to the current SCID.
25 Next the DMA determines {202} if any of the program component processors, including the smart card and μ PC are requesting data or read/write (R/W) access to the memory 18. If no data requests are made on the DMA the process returns to step {200}. If a data R/W request has been made, the DMA determines {203} the
30 priority of the request. This will be accomplished by a conventional interrupt routine or alternatively, by sequential one byte service in an arbitrary order of those program processors requesting data. For example, assume that an arbitrary order of access priority is video, audio I, audio II, smart card, and μ PC.
35 Assume also that only the video, audio II and μ PC are requesting memory access. During the current operation of step {203} a byte

of video will be read from memory. During the next operation of step {203} a byte of audio II will be read from memory, and
5 During the next subsequent occurrence of step {203} a byte of μ PC data will be written to- or read from memory 18 and so forth. Note that addresses for smart card and μ PC access are provided by the smart card and μ PC respectively, but addresses for video, audio and program guide are available from the address pointer
10 arrangement (80-93).

Once priority access has been established {203}, the requisite program processor is serviced {204} with one byte of data written to- or read from memory 18. Next a byte of data from the decryptor 16 is written {205} to memory. A check {206}
15 is made to determine if the μ PC is requesting access. If the μ PC is requesting access, it is serviced {207} with one byte of data. If the μ PC is not requesting access the process jumps to step {202} to determine if any of the program processors are requesting access. In this manner the incoming data is always guaranteed access to
20 every other memory access period, and the intervening memory access periods are spread amongst the program processors.

If data is not presently available from the decryptor 16, i.e. an SCID is not currently detected, the process {208-216} is followed. First the smart card is examined {208} to determine if it
25 is requesting memory access. If it is, it is given a one byte memory access {209}, else a check is made {210} to determine if any of the program processors is requesting memory access. If a data R/W request has been made, the DMA determines {211} the priority of the request. The appropriate processor is serviced
30 {212} with a one byte memory read or write access. If a data R/W request has not been made by the program processors, the process jumps to step {213} where a test is performed to determine if the smart card is requesting memory access. If it is it is serviced {216} with a one byte memory access, else the
35 process jumps to step {200}.

It should be recognized that in the present preferred example, when in the "FEC Not Providing Data" mode, the smart
5 card is provided a two-to-one access precedence over all other program processors. This priority is programmed into a programmable state machine within the DMA apparatus and is subject to being changed by the μ PC. As mentioned earlier, the system is intended to provide interactive services, and the μ PC 19
10 will be responsive to interactive data to perform at least in part the interactive operation. In this role, the μ PC 19 will use the memory 18 both for application storage and working memory. In these instances, the system operator may change the memory access priority to provide the μ PC 19 with memory access of
15 greater frequency. The reprogramming of memory access priority may be included as a subset of interactive application instructions.

It is advantageous to insert media error codes into the video component signal stream when packets are lost, to condition the video signal decompressor to suspend decompression until a
20 particular signal entry point occurs in the data stream. It is not practical to predict where and in which video packet the next entry point may occur. In order to find the next entry point as fast as possible, it is necessary to include a media error code at the beginning of the first video packet after detection that a
25 packet is lost. The circuitry of FIGURE 7 places a media error code at the beginning of every video packet and then excises the media error code in respective packets if there is no loss of a preceding packet. The media error code is inserted in the first M memory address locations reserved for the current video packet payload,
30 by writing to memory 18 for M write cycles prior to the video payload arriving from the decryptor. Concurrently the multiplexor 99 is conditioned by the DMA 98, to apply the media error code from the source 100 to the memory 18 I/O. M is simply the integer number of memory locations required to store the media
35 error code. Assuming the memory to store 8-bit bytes, and the media error code to be 32 bits, M will equal 4.

The addresses for loading the media error code in memory are provided by the respective video component service register 83 via the multiplexer 82 and multiplexer 85. It will be appreciated that the first M addresses provided from the pointer register 83 for loading the media error code into the memory locations that would otherwise be loaded with video component data, will simply be the next M sequential addresses that would normally be produced by the video head pointer. These same addresses are coupled into an M-stage delay element 84, so that immediately after the last byte of the media error code is stored in the memory 18, the first of the M addresses is available at the output of the delay element 84.

The timing of the loading of the media error code into memory coincides with the determination of a lost packet. Packet error or loss detection is performed by an error detector 101 which is responsive to the CC and HD data of the current packet.

If a packet loss is detected, the video component of the current packet is stored in memory 18, starting at the next or (M+1)th address location. This is accomplished by conditioning the multiplexer 85 to continue to pass undelayed head pointers from the appropriate register 83. Alternatively, if a packet loss is not detected, the first M bytes of the video component in the current packet are stored in the memory locations in which the media error code was immediately previously stored.

Packet error or loss detection is performed by an error detector 101 which is responsive to the CC and HD data of the current packet. The detector 101 examines the continuity count CC in the current packet to determine if it differs from the CC of the previous packet by one unit. In addition the TOGGLE bit in the current packet is examined to determine if it exhibits the proper state for the respective video frame. If the CC value is incorrect, the state of the TOGGLE bit is examined. Depending if one or both of the CC and TOGGLE bit are in error, first or second modes of error remediation are instituted respectively. In the second

mode, initiated by both CC and TOGGLE bits being erroneous, the system is conditioned to reset to a packet containing a picture
5 layer header. In the first mode, where only the CC is erroneous, the system is conditioned to reset to a packet containing a slice layer header. (A slice layer is a subset of compressed data within a frame.) In both the first and second modes, the media error code written to memory is retained in the respective payload to
10 alert the decompressor to institute remedial action.

It has been found to be particularly efficient to partition the system such that the SCID detector, the decryptor, the addressing circuitry, the conditional access filter, and the smart card interface are all included on a single integrated circuit.
15 This limits the number of external paths which may lead to critical timing constraints.

CLAIMS

- 5 1. A method of transmitting conditional access information including entitlement management and control data comprising:
- forming N-byte conditional access codes;
 concatenating M different N-byte conditional access
10 codes;
 selecting one of said N-byte conditional access codes or a special N-byte code of predetermined logic state;
 forming a payload including a) said selected one of said N-byte conditional access codes or said special N-byte code,
15 b) concatenating the selected code with said M different N-byte conditional access codes and c) concatenating the concatenated codes with said entitlement management and control data; and
 forming a transport packet having a) a header
 identifying such transport packet as containing entitlement data,
20 and b) said payload.
2. The method set forth in claim 1 further including:
 providing an $(M+1)$ times N byte code in which R
 groups of N-bytes all have bits in a predetermined logic state (R,
25 M, N all integers and R times N is less than or equal to $(M+1)$ times N), and wherein the step of forming a payload comprises ;
 a) selecting one of said N-byte conditional access codes or an N-byte code of all one logic state, b) concatenating the
 selected code with said M different N-byte conditional access
30 codes and c) selecting said $(M+1)$ times N byte code or the concatenated code and d) concatenating the last selected code with
 said entitlement management and control data; and

27

3. Apparatus in a packet signal receiver for processing entitlement data included in signal packets having a header
5 identifying such packets as containing entitlement data, and having a payload having said entitlement data and a payload header including a conditional access code, said apparatus comprising:

10 means (10-12) for applying said packet signal;
a transport processor (13-15,19), responsive to said packet signal, for selecting signal packets identified as containing entitlement data, and extracting payloads from selected packets;
memory means (17,18) for storing extracted payload data as it is received;
15 a conditional access filter (30) arranged to examine payload header data of extracted payloads for subscriber specific conditional access codes, and on failure of detection of a subscriber specific payload inhibiting storing of extracted payload data in said memory means.

20

4. The apparatus set forth in claim 3 further including a smart card coupled to said memory means for utilizing entitlement data stored in said memory means from respective
said payloads having entitlement data.

25

5. The apparatus set forth in claim 3 wherein said conditional access filter comprises;

a register for storing a N-byte subscriber specific conditional access code;
30 means, including a comparator, for comparing said payload header data in exclusive N-byte groups, with said N-byte subscriber specific conditional access code contained in said register, and if a match is made of said subscriber specific conditional access code with any of said exclusive N-byte groups,
35 generating an enable signal to write said entitlement data to said memory means.

6. The apparatus set forth in claim 3 wherein said conditional access filter comprises:

5 a register for storing a N-byte subscriber specific conditional access code;

 means, including a comparator for,

 a) determining if the first N-bytes of said
payload header data contain a code of all one logic state;
10 b) if said first N-bytes do contain a code of all one logic state, comparing N-1 bytes of said subscriber specific conditional access code with said payload header data in exclusive N-byte groups, and if a match is made of N-1 bytes of said
15 subscriber specific conditional access code with N-1 bytes of any of said exclusive N-byte groups, generating an enable signal to write said entitlement data to said memory means;

 c) else comparing said payload header data in exclusive N-byte groups, with said N-byte subscriber specific conditional access code contained in said register, and if a match is
20 made of said subscriber specific conditional access code with any of said exclusive N-byte groups, generating an enable signal to write said entitlement data to said memory means.

7. The apparatus set forth in claim 6 further including
25 a detector for detecting if a predetermined number of N-byte groups of said conditional access code in said payload header data are of like logic state, and if so, generating said enable signal.

8. The apparatus set forth in claim 6 further including
30 a detector for detecting if a predetermined number of N-byte groups of said conditional access code in said payload header data have all zero valued bits, and if so, generating said enable signal.

9. The apparatus set forth in claim 3 further including a detector for detecting if all bytes of said conditional access code in said payload header data are of like logic state, and if all bytes of said conditional access code in said payload header data are of like logic state, generating an enable signal to write payload entitlement data to said memory means.

10. The apparatus set forth in claim 5 wherein said register for storing a N-byte subscriber specific conditional access code comprises N 1-byte registers, and said conditional access filter further comprises:

A multiplexer having N input ports respectively coupled to said N 1-byte registers;
counting circuitry for conditioning said multiplexer to scan its input ports to sequentially provide data from said N 1-byte registers, to said means including a comparator.

11. The apparatus set forth in claim 3 wherein said conditional access filter is programmable to perform a dual function of detecting conditional access codes in a first mode and detecting video component start codes in a second mode.

12. The apparatus set forth in claim 11 wherein said conditional access filter comprises;

a register for storing a N-byte subscriber specific conditional access code;
a register for storing a N-byte video component start code;

a multiplexer, responsive to a control signal for selecting one of said subscriber specific conditional access code or said video component start code;

means, including a comparator, coupled to said multiplexer, for comparing said payload header data in N-byte groups, with said N-byte subscriber specific conditional access

30

code or said video component start code selected by said multiplexer, and if a match is made of said subscriber specific
5 conditional access code with an N-byte group of the payload header, generating an enable signal to write said entitlement data to said memory means, or if a match is made of said video component start code with an N-byte group of the payload header, generating an start code indicating signal.

10

13. The apparatus set forth in claim 12 wherein said means, including a comparator is arranged to functionally perform, in said first mode;

a) determining if the first N-bytes of said
15 payload header data contain a code of all one logic state;

b) if said first N-bytes do contain a code of all one logic state, comparing N-1 bytes of said subscriber specific conditional access code with said payload header data in exclusive N-byte groups, and if a match is made of N-1 bytes of said
20 subscriber specific conditional access code with N-1 bytes of any of said exclusive N-byte groups, generating an enable signal to write said entitlement data to said memory means;

c) else comparing said payload header data in exclusive N-byte groups, with said N-byte subscriber specific
25 conditional access code contained in said register, and if a match is made of said subscriber specific conditional access code with any of said exclusive N-byte groups, generating an enable signal to write said entitlement data to said memory means.

30

1 / 7




FIG. 1




FIG. 2




FIG. 8

2/7




FIG. 3

SUBSTITUTE SHEET (RULE 26)

3/7




FIG. 4

SUBSTITUTE SHEET (RULE 26)

4/7




FIG. 5

5/7




FIG. 6




FIG. 7




FIG. 9

SUBSTITUTE SHEET (RULE 26)

INTERNATIONAL SEARCH REPORT

International Application No
PCT/US 95/03540

A. CLASSIFICATION OF SUBJECT MATTER
IPC 6 H04N7/16 H04N7/167

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)
IPC 6 H04N

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	BBC RESEARCH DEPARTMENT REPORT, no. 10, August 1988 TADWORTH, SURREY, UK, pages 1-18, D.T. WRIGHT 'CONDITIONAL ACCESS BROADCASTING: DATACARE 2'	1,3
A	see page 1, right column, line 30 - page 5, left column, line 5 see page 6, left column, line 28 - page 14, left column, line 49 ---	2,4-13
A	EP,A,0 582 122 (MATSUSHITA) 9 February 1994 see page 4, column 6, line 47 - page 5, column 8, line 27 see figures 1,2,8 --- -/--	1-13

☒ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents :

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier document but published on or after the international filing date

"I" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

"&" document member of the same patent family

Date of the actual completion of the international search

5 July 1995

Date of mailing of the international search report

18. 07. 95

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+ 31-70) 340-2040, Tx. 31 651 epo nl,
Fax: (+ 31-70) 340-3016

Authorized officer

Van der Zaal, R

INTERNATIONAL SEARCH REPORT

Internatic Application No
PCT/US 95/03540

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	WO,A,85 00718 (INDEPENDENT BROADCASTING AUTHORITY) 14 February 1985 see page 3, line 30 - page 5, line 28 see figures 1-4 <div style="text-align: center;">---</div>	1-13
A	EP,A,0 256 596 (PHILIPS) 24 February 1988 see page 4, column 5, line 39 - page 9, column 6, line 35 see figures 2-7 <div style="text-align: center;">-----</div>	1-13

INTERNATIONAL SEARCH REPORT

Information on patent family members

Internatio Application No
PCT/US 95/03540

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
EP-A-582122	09-02-94	JP-A- 6303608	28-10-94
		JP-A- 6303609	28-10-94
		JP-A- 6069916	11-03-94
		JP-A- 6090451	29-03-94
		US-A- 5377266	27-12-94
		CN-A- 1085724	20-04-94
WO-A-8500718	14-02-85	DE-A- 3470646	26-05-88
		DE-A- 3474496	10-11-88
		EP-A,B 0151147	14-08-85
		EP-A,B 0148235	17-07-85
		WO-A- 8500491	31-01-85
		JP-B- 5025436	12-04-93
		JP-T- 60501882	31-10-85
		US-A- 4736422	05-04-88
		US-A- 4802215	31-01-89
EP-A-256596	24-02-88	DE-D- 3789178	07-04-94
		DE-T- 3789178	25-08-94
		GB-A- 2193867	17-02-88
		JP-A- 63048028	29-02-88
		US-A- 4937866	26-06-90